

# JustLED Stretch LED Downlight Fitting SD-13-UP-Series

Fitting Colour : White = WW, Chrome = CH,

## Please read instructions before commencing installation and retain for future reference.

This IP20 Stretch LED downlighter has been designed to be both functional and decorative. This product is suitable for indoor use only. The box contains the light fitting and driver. The box is recyclable.

### SPECIFICATION

A high quality cast fitting with either a white or superior chrome finish.

This fitting's driver is Class 2 Double-insulated and must not be earthed.

Supply is 100-240 volts at 50/60Hz.	Light source 13W COB	Beam Angle : 60°
Size : Ø96 x H67mm	This fitting is IP20	Ra : >80
3000 Kelvins : 950 Lumens	Hole size is 80mm	
5000 Kelvins : 1000 Lumens	RoHS Compliant	CE Approved

Complies with BS61347-1 / 2-13 BS : 62493 / 55015 / 61547 / 61000-3-2 / 3-3

### INSTALLATION

1. Prior to any electrical work, isolate the electrical supply and check it dead!
2. Check all parts are present and undamaged. Do not install damaged items.
3. Do not install in wet/damp plaster.
4. Cut a 80mm hole in the ceiling ensuring no cables/pipes/joists behind.
5. Connect the (isolated) mains supply to the driver ensuring the colour coding/polarity are followed correctly.
6. Connect the fitting to the driver ensuring the plug and socket are correctly located and locked off. NEVER CONNECT/DISCONNECT DRIVER WITH THE SUPPLY SWITCHED ON!!
7. Fold the two spring clips inwards and locate into the hole. Push the fitting home until sitting flush with the ceiling.
8. Turn on the electrical supply and test fitting works correctly.
9. This fitting should be installed by a qualified electrician to the latest IEE Regulations, British Standards and Building Regulations.

### SAFETY

1. Never start work until the electricity supply is isolated and checked dead!
2. Do not cover the fitting with insulation material.
3. Always adhere to the latest IEE Regulations, British Standards and Building Regulations.
4. Never use any part which shows any sign(s) of damage.

### CARE AND MAINTENANCE

1. Always isolate the electrical supply and check it dead, prior to any maintenance or repair work.
2. Allow fitting to cool down prior to maintenance / repair work.
3. The face of this product can be cleaned with a lightly dampened cloth. No chemicals should be used.

### Information for the product user

1. Please note the requirement to dispose of Waste Electrical & Electronic Equipment separately from household waste (WEEE marked with crossed out wheelie bin symbol).
2. Please consider your role in contributing to re-use and recycling by returning this product at end of life to a collection centre for waste electrical equipment or a Civic Amenity site, or to the retail outlet from which you are purchasing a replacement.
3. This equipment may contain substances that are hazardous to health and the environment if disposed of carelessly. It is important that it is separated from normal household waste and recycled in the WEEE chain.
4. The "crossed out wheelie bin symbol" on a product indicates this equipment must not be disposed of in normal household waste, but should be disposed of according to local WEEE regulations.

### JustLED Lighting Ltd

Unit 27, Regent Trade Park  
Barwell Lane, Gosport  
PO13 0EQ

Tel : (0) 1329 287 822  
Email : info@justled.co  
Website : www.justled.co

