

JustLED GU10 240V IP65 Fire Rated Downlight Fitting DL-01-GU

Please read instructions before commencing installation and retain for future reference.

This IP65 Fire Rated downlight has been designed to be both functional and decorative. This product is suitable for indoor use only. The box contains the light fitting complete with bezel. The box is recyclable.

SPECIFICATION

A pressed steel fitting with die-casting aluminium bezel with intumescent seal giving 90 minutes fire protection when installed in an appropriate ceiling complies with BS 476 : Part 21

This fitting must be earthed.

Supply is 230-240 volts at 50Hz.

Hole size is 72mm.

Size : Ø87 x H108mm

CE Approved.

Maximum 50 watts lamp.

This fitting is IP65

RoHS Compliant.

INSTALLATION

1. Prior to any electrical work, isolate the electrical supply and check it dead!
2. Check all parts are present and undamaged. Do not install damaged items.
3. Do not install in wet/damp plaster.
4. Cut a 72mm hole in the ceiling ensuring no cables/pipes/joists behind.
5. Connect the (isolated) mains supply to the fitting ensuring the colour coding/polarity are followed correctly.
6. Fold the two spring clips inwards and locate into the hole. Push the fitting home until sitting flush with the ceiling.
7. Fit the lamp to the fitting and to the bezel; fit the bezel.
8. Turn on the electrical supply and test fitting works correctly.
9. This fitting should be installed by a qualified electrician to the latest IEE Regulations, British Standards and Building Regulations.

SAFETY

1. Never start work until the electricity supply is isolated and checked dead!
2. Do not cover the fitting with insulation material.
3. Always adhere to the latest IEE Regulations, British Standards and Building Regulations.
4. Never use any part which shows any sign(s) of damage.

CARE AND MAINTENANCE

1. Always isolate the electrical supply and check it dead, prior to any maintenance or repair work.
2. Allow fitting to cool down prior to maintenance / repair work.
3. The face of this product can be cleaned with a lightly dampened cloth. No chemicals should be used.

Information for the product user

1. Please note the requirement to dispose of Waste Electrical & Electronic Equipment separately from household waste (WEEE marked with crossed put wheelie bin symbol).
2. Please consider your role in contributing to re-use and recycling by returning this product at end of life to a collection centre for waste electrical equipment or a Civic Amenity site, or to the retail outlet from which you are purchasing a replacement.
3. This equipment may contain substances that are hazardous to health and the environment if disposed of carelessly. It is important that it is separated from normal household waste and recycled in the WEEE chain.
4. The "crossed out wheelie bin symbol" on a product indicates this equipment must not be disposed of in normal household waste, but should be disposed if according to local WEEE regulations.

JustLED Lighting Ltd

Unit 27, Regent Trade Park
Barwell Lane, Gosport
PO13 0EQ

Tel : (0) 1329 287 822
Email : info@justled.co
Website : www.justled.co

